

Maretron Cloud Services (RTCS & TCS) connecting with Starlink

Maretron Cloud Services & Starlink


With the latest installment of Starlink systems, the DNS directory may still be incomplete, which may block the Maretron external connections, i.e. Real Time Cloud Service (RTCS) and Telemetric Cloud Service (TCS).

DNS, or the **Domain Name System**, translates human readable domain names (for example, www.amazon.com) to machine readable IP addresses (for example, 192.0.2.44).

The following guide will allow the user to set a Custom DNS directory to use for this service **8.8.8.8** (Google).

** This can also be completed using Cloudflare DNS at 1.1.1.1.*


1. Open the Starlink App and Navigate to the Settings Menu




2. When you open the settings menu, the router settings should be selected by default.

* If you're in the Starlink dish settings instead, simply slide the selector from Starlink to Router.

Select **Custom DNS** under the Advanced options.



3. Once in the Custom DNS menu, toggle on the option to Enable Custom DNS. It will be blue when turned on and show you entry fields for primary and backup DNS addresses.
4. Enter the following DNS Address entries as below, then press Save.
 - Primary **8.8.8.8**
 - Secondary **8.8.4.4**



CONTENT FILTERING

Enable Custom DNS

Custom DNS allows you to specify IPv4 or IPv6 addresses for one or more alternate DNS servers to be used for lookups instead of the Starlink defaults.

Primary

1.1.1.1



Required


Backup

1.0.0.1

2606:4700:4700::1111

2606:4700:4700::1001

SAVE



Online URL:

<https://www.maretron.com/wp-content/phpkbv96/article.php?id=735>